

DHI-ART-ARC3800H-03-FW2

Dahua Wireless Alarm KIT



Series Overview

The Alarm Kit contains all the products required for a basic wireless alarm system, providing you and your assets with strong protection.

Scene

Mainly applied for villas, shops, apartments, etc.

Technical Specification		
Port		
Wireless Zone	Hub: 150 channels wireless peripherals (6 sirens, 64 PIR cameras, 64 keyfobs, 8 keypads and 4 repeaters)	
Network Mode	LM: Supports installation of dual SIM cards. Only one card can be enabled at a time. Also, multiple frequency bands are supported for the SIM cards (GSM: 850/900/1800/1900 MHz, WCDMA:B1/B2/B4/B5/B8, LTE-FDD:B1/B2/B3/B4/B5/B7/B8/B28, LTE-TDD: B40). EU: Supports installation of dual SIM cards. Only one card can be enabled at a time. Also, multiple frequency bands are supported for the SIM cards (GSM: 900/1, 800 MHz, WCDMA: B1/B8, LTE-FDD: B1/B3/B7/B8/B20/B28A, LTE-TDD:B38/B40/B41).	
Network Port	Hub: 1 RJ-45, 10 Mbps/100 Mbps Ethernet port.	
Storage Battery	Hub: One built-in 4,750 mAh rechargeable lithium battery.	
Video & Audio		
Video Input	Hub: 8-ch IPC, which only supports the upload of alarm videos.	
Audio Output	Hub: 1 channel	
Volume Control	Hub: Yes	
Voice Broadcast	Hub: Telephone and local speaker	

- Supports alarm video verification through integration of the IPC with the hub.
- Images can be remotely and quickly transferred from the PIR-Cam to the device.
- · Features voice call alarm.
- Supports wired and AP network configuration methods, which makes it easier to add the hub to apps and to switch to the hub's network
- Supports multi-network redundancy for Ethernet, Wi-Fi and 4G networks to ensure the network remains stable and reliable.
- Supports two-way communication and frequency hopping to make communication with wireless peripherals stable and reliable.
- Features cloud update. You can also remotely update the device and wireless peripherals on the mobile app.
- Offers a dual backup system, and uses auto recovery when an update fails.

Function

Hub: The indicator indicates the status of alarms, arming and disarming, the network connection and device failure. Keyfob: 1 dual-color status indicator (Green means normal and red means abnormal) Door Detector: 1 green alarm indicator PIR Detector: 1 green alarm indicator PIR Detector: 1 green alarm indicator PIR Detector: 1 power switch button. Keyfob: 4 (Home, Away, Disarm, and SOS) Door Detector: 1 power switch PIR Detector: 2 power switch PIR Detector: 3 power switch PIR Detector: 4 power switch PIR Detector: 1 power switch	1 directori		
switch button. Keyfob: 4 (Home, Away, Disarm, and SOS) Door Detector: 1 power switch PIR Detector: 1 power switch SMS Hub: Yes (up to 5 phone numbers) Phone Call Hub: Yes (up to 5 phone numbers) Video Linkage Hub: Yes Hub: Stores up to 50 alarm messages. Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Tamper Hub: Yes Door Detector: Yes PIR Detector: Yes PIR Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Indicator Light	and disarming, the network connection and device failure. Keyfob: 1 dual-color status indicator (Green means normal and red means abnormal) Door Detector: 1 green alarm indicator	
Phone Call Hub: Yes (up to 5 phone numbers) Video Linkage Hub: Yes Offline Cache Hub: Stores up to 50 alarm messages. Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Tamper Hub: Yes Door Detector: Yes PIR Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Button	switch button. Keyfob: 4 (Home, Away, Disarm, and SOS) Door Detector: 1 power switch	
Video Linkage Offline Cache Hub: Stores up to 50 alarm messages. Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Hub: Yes Door Detector: Yes PIR Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	SMS	Hub: Yes (up to 5 phone numbers)	
Offline Cache Hub: Stores up to 50 alarm messages. Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Hub: Yes Door Detector: Yes PIR Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Phone Call	Hub: Yes (up to 5 phone numbers)	
Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Hub: Yes Door Detector: Yes PIR Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Video Linkage	Hub: Yes	
Arm and Disarm arming and disarming. All: Cloud update Low Battery Detection All: Yes Hub: Yes Door Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Offline Cache	Hub: Stores up to 50 alarm messages.	
Low Battery Detection All: Yes Hub: Yes Door Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Arm and Disarm		
Tamper Hub: Yes Door Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Remote Update	All: Cloud update	
Tamper Door Detector: Yes PIR Detector: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users	Low Battery Detection	All: Yes	
User Management installer) and 32 keypad users	Tamper	Door Detector: Yes	
Logs Hub: Up to 5, 000 entries	User Management	installer) and	
	Logs	Hub: Up to 5, 000 entries	

Alarm Kit | DHI-ART-ARC3800H-03-FW2

Alaminite Dill	711171110300011 03 1 112	
Measuring Range (Temperature)	Door Detector: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) PIR Detector: -15 °C to +65 °C (+5 °F to +149 °F) (indoor)	
Transmission Protocol	Hub: SIA, SoftGuard	
Technical		
Sensor	Door Detector: Reed switch PIR Detector: Dual elements low-noise PIR sensor	
Detection Mode	PIR Detector: PIR	
Sensitivity	PIR Detector: 3 levels adjustable	
Detection Range	PIR Detector: 12 m (39.37 ft) (90°) with installation height of 2.2 m (7.21 ft)	
Detection Speed	PIR Detector: 0.3 m/s–3 m/s (0.98 ft/s–9.84 ft/s)	
Movement Distance	Door Detector: < 40 mm (1.57")	
Pet Immunity Level	PIR Detector: ≤ 18 kg (39.68 lb)	
White Light Resistance Level	PIR Detector: 6500 lx	
Two-way Digital Temperature Compensation	PIR Detector: Yes, no attenuation of detection distance in high temperature.	
Scenario	Door Detector: Non-metal doors	
Wireless		
Carrier Frequency	All: 433.1 MHz–434.6 MHz	
Communication Mechanism	All: Two-way	
Communication Distance	Hub: Up to 1,400 m (4593.18 ft) in an open space. Keyfob: Up to 500 m (1640.42 ft) in an open space. Door Detector: Up to 1,000 m (3280.84 ft) in an open space. PIR Detector: Up to 1,200 m (3937.01 ft) in an open space.	
Encryption Mode	All: AES128	
Frequency Hopping	All: Yes	
Wi-Fi	Hub: 2.4G	
General		
Language	Up to 7 languages are supported for SMS: English, Spanish (Latin America), French, Italian, Arabic, Turkish, and Danish. It is set as English by default. The alarm voice message feature and local speaker support English and Italian.	
Power Supply	Hub: 100-240 VAC, 50/60 HZ Keyfob: CR2032 battery Door Detector: CR123A battery PIR Detector: CR123A battery	
Standby Time	The battery lasts up to 12 hours when it is fully charged and is within the following conditions: It is connected to the Wi-Fi, its ID is connected to the alarm receiving center, the heartbeat interval is 1,800 seconds, and it is connected to 8 peripherals and the cloud. Keyfob: 3 years Door Detector: 4 years PIR Detector: 4 years	
Power Consumption	Hub: Max. 12 W Keyfob: Max. 100 mW Door Detector: Max. 125 mW PIR Detector: Max. 120 mW	
Operating Temperature	All: -10 °C to +55 °C (+14 °F to +131 °F) (indoor)	

Operating Humidity	All: 10%–90% (RH)	
Product Dimensions	Hub: 174.8 mm × 174.8 mm × 38.3 mm (6.88" × 6.88" × 1.51") (L × W × H) Keyfob: 60.0 mm × 39.5 mm × 15.0 mm (2.36" × 1.56" × 0.59") (L × W × H) Door Detector: 100.2 mm × 20.8 mm × 20.3 mm (3.94" × 0.82" × 0.80") (L × W × H) PIR Detector: 104.0 mm × 60.0 mm × 50.0 mm (4.09" × 2.36" × 1.97") (L × W × H)	
Net Weight	Hub: 510 g (1.12 lb) Keyfob: 20 g (0.04 lb) Door Detector: 70 g (0.15 lb) PIR Detector: 100 g (0.22 lb)	
Gross Weight	Kit: 1.46 kg (3.22 lb)	
Installation	Hub: Wall mount; Desktop mount Door Detector: Bracket mount PIR Detector: Wall mount	
Casing Material	All: PC + ABS	
Certifications	All: CE	
Anti-corrosion Level	Basic Protection	
Storage Temperature	All: -10 °C to +55 °C (+14 °F to +131 °F)	
Storage Humidity	All: 10%-90% (RH)	
Packaging Dimensions	Kit: 270 mm \times 218 mm \times 122 mm (10.63" \times 8.58" \times 4.80") (L \times W \times H)	

Ordering Information				
Туре	Model	Description		
Alarm KIT	DHI-ART-ARC3800H-03-FW2	Dahua Wireless Alarm KIT		

Application



Rev 002.000 © 2024 Dahua. All rights reserved. Design and specifications are subject to change without notice. Pictures in the document are for reference only, and the actual product shall prevail.