

EZ-HAC-B1A21

2MP HDCVI IR Bullet Camera

HDCVI



- · Max. 25/30fps@1080P
- · HD and SD output switchable
- · 3.6mm fixed lens (2.8mm, 6mm optional)
- · Max. IR length 20m, Smart IR
- · IP67, DC12V













System Overview

Experience 1080P full HD video and the simplicity of using existing cabling infrastructure with HDCVI. The EZIP series 1080P HDCVI camera features a compact design and offers a high quality image at a friendly price. It offers various vari-focal/fixed lens models with a multi-language OSD and HD/SD switchable output. Its structural flexibility and high cost-performance makes the camera an ideal choice for SMB solutions.

Functions

4 Signals over 1 Coaxial Cable

HDCVI technology supports 4 signals to be transmitted over 1 coaxial cable simultaneously, i.e. video, audio*, data and power. Dual-way data transmission allows the HDCVI camera to interact with the HCVR, such as sending control signal or triggering alarm. Moreover, HDCVI technology supports PoC for construction flexibility.

* Audio input is available for some models of HDCVI cameras.

Long Distance Transmission

HDCVI technology guarantees real-time transmission at long distance without any loss. It supports up to 800m(1080P)/1200m(720P) transmission via coaxial cable, and up to 300m(1080P)/450m(720P) via UTP cable.*

*Actual results verified by real-scene testing in Dahua's test laboratory.

Simplicity

HDCVI technology inherits the born feature of simplicity from traditional analog surveillance system, making itself a best choice for investment protection. HDCVI system can seamlessly upgrade the traditional analog system without replacing existing coaxial cabling. The plug and play approach enables full HD video surveillance without the hassle of configuring a network.

Smart IR

The camera is designed with microcrystalline LED IR illumination for best lowlight performance. Smart IR is a technology to ensure brightness uniformity in B/W image under low illumination. Dahua's unique Smart IR adjusts to the intensity of camera's infrared LEDs to compensate for the distance of an object, and prevents IR LEDs from overexposing images as the object come closer to the camera.

Multi-formats

The camera supports multiple video formats including HDCVI, CVBS and other two common HD analog formats in the market. The four formats can be switched over through OSD menu or by PFM820(UTC controller). This feature makes the camera to be compatible with not only HCVRs but also most end users' existing HD/SD DVRs.

Multi-language OSD

OSD menu provides multiple image adjustments and function settings to meet the requirements of different monitoring scenes. The OSD menu includes configurations such as backlight mode, day/night, white balance, privacy mask and motion detect. The camera supports 11 languages for OSD menu, namely, Chinese, English, French, German, Spanish, Portuguese, Italian, Japanese, Korean, Russian and Polish.

Protection

The camera's outstanding reliability is unsurpassed due to its rugged design. The camera is protected against water and dust with IP67 ranking, making it suitable for indoor or outdoor environments.

With working temperature range of -40°C to +60°C (-40°F to +140°F), the camera is designed for extreme temperature environments.

Supporting $\pm 30\%$ input voltage tolerance, this camera suits even the most unstable power supply conditions. Its 4KV lightning rating provides protection against the camera and its structure from the effects of lightning.

EZIP Series | EZ-HAC-B1A21

<u>'</u>		
Technical Specification	n	Day/Nigh
Camera		OSD Men
Image Sensor	1/2.7" CMOS	BLC Mod
Effective Pixels	1920(H)×1080(V), 2MP	WDR
Scanning System	Progressive	Gain Con
Electronic Shutter Speed	PAL: 1/25~1/100000s NTSC: 1/30~1/100000s	Noise Re
Minimum Illumination	0.04Lux/F1.85, 30IRE, 0Lux IR on	White Ba
S/N Ratio	More than 65dB	Smart IR
IR Distance	Up to 20m (66feet)	Certific
R On/Off Control	Auto / Manual	- 10
Lens		Certificat
Lens Type	Fixed lens / Fixed iris	Interfa
Mount Type	Board-in	Audio Int
Focal Length	3.6mm (2.8mm, 6mm Optional)	Eelectr
Max Aperture	F1.85	Power Su
Angle of View	H: 93° (103°, 54.7°)	Power Co
Focus Control	N/A	Enviror
Close Focus Distance	800mm (500mm, 2000mm) 31.50" (19.69", 78.74")	Operatin
DORI Distance		Storage C
Note: The DORI distance is a "general proximity" of distance which makes it easy to pinpoint the right camera for your needs. The DORI distance is calculated based on		Ingress P Resistand
sensor specification and lab test	result according to EN 62676-4 which defines the ognize and Identify respectively.	Constr

	DORI Definition	Distance
Detect	25px/m (8px/ft)	2.8mm: 37m(121ft) 3.6mm: 51m(167ft) 6mm: 80m(262ft)
Observe	63px/m (19px/ft)	2.8mm: 15m(49ft) 3.6mm: 20m(66ft) 6mm: 32m(105ft)
Recognize	125px/m (38px/ft)	2.8mm: 8m(26ft) 3.6mm: 10m(33ft) 6mm: 16m(52ft)
Identify	250ppm (76px/ft)	2.8mm: 4m(14ft) 3.6mm: 5m(17ft) 6mm: 8m(26ft)

Pan / Tilt / Rotation

Pan/Tilt/Rotation	Pan: 0° ~ 360° Tilt: 0° ~ 90° Rotation: 0° ~ 360°

Video

Resolution	1080P (1920×1080)
Frame Rate	25/30fps@1080P, 25/30/50/60fps@720P
Video Output	1-channel BNC high definition video output / CVBS video output (Can switch)

Day/Night	Auto (ICR) / Manual
OSD Menu	Multi-language
BLC Mode	BLC / HLC / DWDR
WDR	DWDR
Gain Control	AGC
Noise Reduction	2D
White Balance	Auto / Manual
Smart IR	Auto / Manual
Certifications	
Certifications	CE (EN55032, EN55024, EN50130-4) FCC (CFR 47 FCC Part 15 subpartB, ANSI C63.4-2014)
Interface	
Audio Interface	N/A
Eelectrical	
Eelectrical Power Supply	12V DC ±30%
	12V DC ±30% Max. 2.7W (12V DC, IR on)
Power Supply	
Power Supply Power Consumption	
Power Supply Power Consumption Environmental	Max. 2.7W (12V DC, IR on) -40°C ~ +60°C (-40°F ~ +140°F) / Less than 95% RH
Power Supply Power Consumption Environmental Operating Conditions	Max. 2.7W (12V DC, IR on) -40°C ~ +60°C (-40°F ~ +140°F) / Less than 95% RH * Start up should be done at above-40°C (-40°F)
Power Supply Power Consumption Environmental Operating Conditions Storage Conditions Ingress Protection & Vandal	Max. 2.7W (12V DC, IR on) $ -40^{\circ}\text{C} \sim +60^{\circ}\text{C} \; (-40^{\circ}\text{F} \sim +140^{\circ}\text{F}) \; / \; \text{Less than 95\% RH} $ * Start up should be done at above-40°C (-40°F) $ -40^{\circ}\text{C} \sim +60^{\circ}\text{C} \; (-40^{\circ}\text{F} \sim +140^{\circ}\text{F}) \; / \; \text{Less than 95\% RH} $
Power Supply Power Consumption Environmental Operating Conditions Storage Conditions Ingress Protection & Vandal Resistance	Max. 2.7W (12V DC, IR on) $ -40^{\circ}\text{C} \sim +60^{\circ}\text{C} \; (-40^{\circ}\text{F} \sim +140^{\circ}\text{F}) \; / \; \text{Less than 95\% RH} $ * Start up should be done at above-40°C (-40°F) $ -40^{\circ}\text{C} \sim +60^{\circ}\text{C} \; (-40^{\circ}\text{F} \sim +140^{\circ}\text{F}) \; / \; \text{Less than 95\% RH} $

0.14kg (0.31lb)

0.17kg (0.37lb)

Net Weight

Gross Weight

EZIP Series | EZ-HAC-B1A21

Ordering Information			
Туре	Part Number	Description	
	EZ-HAC-B1A21P-0280B		
	EZ-HAC-B1A21P-0360B	2MP HDCVI IR Bullet Camera, PAL	
2MP Camera	EZ-HAC-B1A21P-0600B		
ZIVIP Calliera	EZ-HAC-B1A21N-0280B		
	EZ-HAC-B1A21N-0360B	2MP HDCVI IR Bullet Camera, NTSC	
	EZ-HAC-B1A21N-0600B		
	PFA134	Junction box (For use alone or with PFA152-E pole mount)	
	PFA152-E	Pole mount (For use with PFA134 junction box)	
Accessories	PFM800-E	Passive HDCVI Balun	
Accessories	PFM321	12V 1A Power Adapter	
	PFM320D-015	12V 1.5A Power Adapter	
	PFM300	12V 2A Power Adapter	
	PFM820	UTC Controller	

PFA134 PFA152-E		
	PFA134	PFB134 + PFA152-E

Accessories

Optional:



PFA134 Junction box



PFA152-E Pole mount



PFM800-E Passive HDCVI Balun



PFM321 12V 1A Power Adapter





PFM320D-015 Power Adapter



PFM300 12V 2A Power Adapter

Junction Mount





Pole Mount



PFM820 UTC Controller

